

8GB Computer memory DDR4 for Gigabyte H310M S2 (rev. 1.0) UDIMM







PHS-memory® - computer memory with 100% quality

- many years of IT competence
- Free support for optimal configuration and product selection
- High availability through professional warehouse management
- Fast delivery in throughout Europe
- Short response times and professional order processing due to full digitalization throughout the entire process with complete traceability
- Incoming goods inspection include checks of the DRAMs, PCBs and the programmed SPDs in order to exclude possible errors (Controlled BOM).
- PHS-memory® brand memories guarantee 100% compatibility to the specified system.
- PHS-memory® memories can be used together with existing memories in the device depends on to the configuration rules of the system.
- The "fallback option" in the SPD of PHS-memory® allows DRAMs with higher clock rates to be operated together with older memory modules with lower clock rates within the system.
- Products with unique serial number for service and warranty
- Pre-sales and after-sales support by technically trained personnel



Memory Specification



Memory size	8GB		
Memory technology	DDR4		
ECC support	no		
JEDEC Norm	PC4-2133P-U		
Туре	UDIMM (Non-ECC unbuffered)		
Number of pins	288 Pin DIMM		
Memory data transfer rate	2133MHz @ CL15		
Voltage	age 1,2 Volt		
Speciality	-		
Board dimensions	133,35 x 31,25 (LxB mm)		
Operating temperature	0° C - 85° C		
Storage temperature	-40° C - +95° C		
RoHS compliant	yes		
SKU	SP325039		
EAN	4063369881365		

Note: The module specified in this datasheet is one of several possible configurations available under this part number.

Some details may differ from the specifications described here and the illustration, but have no negative influence on the functionality.



System Specifications

The memory is 100% compatible with this sytem:

System manufacturer	Gigabyte
Device type	Motherboard-memory
Device family	Mainboard H
Device series	H310M Serie
Device name	H310M S2 (rev. 1.0)
Maximum memory*	64GB / 32GB according to manufacturer
Number of memory sockets	2

^{*} The specifications for the maximum memory upgrade may differ from those of the manufacturer Gigabyte. Often the information given in the manual for the maximum memory upgrade is not up to date. New memory technologies, bios updates or newer software versions often allow the use of memory modules with a higher capacity than specified by the manufacturer with the same performance and stability.

Information on memory allocation

What should be considered when upgrading RAM?

- Der schnelle Dual Channel Mode Betrieb wird bei der paarweisen Installation der memory optimal supports
- If you have a Core i5 or Core i7 processor, you can only use the UDIMM memory
- If you are using a Xeon processor, you can use ECC UDIMM memory or UDIMM memory without ECC
- Die ECC Funktion wird nur dann supports, wenn alle eingesetzten Computer memory UDIMM ECC memory sind.

Information on memory installation

- Turn off the system
- Remove the plug of the power supply unit (if connected)
- Remove the battery, according to the user manual of the system
- Always ground yourself before touching electronic components
- Protect the memory module from static voltages:
 - Do not touch the gold pins of the memory module
 - Only touch the sides of the memory module
 - Use a grounding strap and/or ESD glove if possible

General installation instructions are supplied by E-Mail.



Further memory options for Gigabyte H310M S2 (rev. 1.0)

Size	SKU	Technology	Туре	Number of pins	Brand	Reference no.
4GB	SP325038	DDR4	UDIMM (Non- ECC unbuffered)	288 Pin DIMM	PHS-memory®	
8GB	SP325039	DDR4	UDIMM (Non- ECC unbuffered)	288 Pin DIMM	PHS-memory®	
16GB	SP325036	DDR4	UDIMM (Non- ECC unbuffered)	288 Pin DIMM	PHS-memory®	
32GB	SP325037	DDR4	UDIMM (Non- ECC unbuffered)	288 Pin DIMM	PHS-memory®	

PHS-memory® warranty

Every PHS-memory® is equipped with a 5-years-warranty of perfect operation. If the RAM module is defective or fails within 5 years of purchase when used properly, you will receive an appropriate RAM module free of charge. If a suitable memory module is no longer available, we will refund the purchase price.

For more information on warranty and service please visit https://www.phs-memory.fr/-W5Y



Contact Information

PHS-electronic gmbh - www.phs-memory.fr -Karl-Götz-Str. 5 97424 Schweinfurt Allemagne Phone: +49 9721 784678 E-Mail: info@phs-memory.fr Web: www.phs-memory.fr

All information without guarantee. Technical changes and errors excepted. You can find current price information in our online shop at https://www.phs-memory.fr