

32GB Computer memory DDR3 for Fujitsu Primergy RX500 S7 RDIMM





Your benefits ✓ verified quality memory ✓ 5 years warranty Warranty details see last page ✓ 100% compatible ✓ free support on our hotline ✓ fast delivery

PHS-memory® - computer memory with 100% quality

- many years of IT competence
- Free support for optimal configuration and product selection
- High availability through professional warehouse management
- Fast delivery in throughout Europe
- Short response times and professional order processing due to full digitalization throughout the entire process with complete traceability
- Incoming goods inspection include checks of the DRAMs, PCBs and the programmed SPDs in order to exclude possible errors (Controlled BOM).
- PHS-memory® brand memories guarantee 100% compatibility to the specified system.
- PHS-memory® memories can be used together with existing memories in the device depends on to the configuration rules of the system.
- The "fallback option" in the SPD of PHS-memory® allows DRAMs with higher clock rates to be operated together with older memory modules with lower clock rates within the system.
- Products with unique serial number for service and warranty
- Pre-sales and after-sales support by technically trained personnel



Memory Specification



Memory size	32GB		
Memory technology	DDR3		
ECC support	yes		
JEDEC Norm	PC3L-12800R		
DRAM Organization	2Gx4		
Rank	4Rx4 (4DRx4 DDP)		
Туре	RDIMM (ECC Registered)		
Number of pins	240 Pin DIMM		
Memory data transfer rate	1600MHz @ CL11		
Voltage	1,35 Volt		
Speciality	DDP		
Board dimensions	133,35 x 30 (LxB mm)		
Operating temperature	0° C - 85° C		
Storage temperature	-40° C - +95° C		
RoHS compliant	yes		
SKU	SP463993		
EAN	4067488275104		

Note: The module specified in this datasheet is one of several possible configurations available under this part number.

Some details may differ from the specifications described here and the illustration, but have no negative influence on the functionality.



System Specifications

The memory is 100% compatible with this sytem:

System manufacturer	Fujitsu	
Device type	Server	
Device family	Primergy	
Device series	RX500 Serie	
Device name	Primergy RX500 S7	
Maximum memory*	1,5TB	
Number of memory sockets	48	

^{*} The specifications for the maximum memory upgrade may differ from those of the manufacturer Fujitsu. Often the information given in the manual for the maximum memory upgrade is not up to date. New memory technologies, bios updates or newer software versions often allow the use of memory modules with a higher capacity than specified by the manufacturer with the same performance and stability.

Information on memory allocation

Information on memory configuration

The following technical specifications should be considered in advance:

- In the device, you can install RDIMM (Registered DIMM) or LRDIMM (Load Reduced DIMM) RAM memory modules. LRDIMM memory is recommended when aiming for large memory capacities.
- RDIMM memory modules cannot be used together with LRDIMM memories.
- If a memory expansion is to be used with existing RAM memories, it must be checked which memory technology (RDIMM / LRDIMM) is already installed in the device.
- Memory slots without a processor may not be used.
- A higher memory clock of the memory module automatically adapts to the memory clock specified by the system. This can be the case especially with larger capacities.
- The low voltage memories with 1.35V are clocked with 1.5V when mixed with 1.5V memories via the fallback option in the memory.
- Each CPU has 4 memory channels with 3 memory slots each.

Information on memory installation

- Turn off the system
- Remove the plug of the power supply unit (if connected)
- Remove the battery, according to the user manual of the system
- Always ground yourself before touching electronic components
- Protect the memory module from static voltages:
- Do not touch the gold pins of the memory module
- Only touch the sides of the memory module
- Use a grounding strap and/or ESD glove if possible

Product Datasheet | SP463993 32GB Computer memory for Primergy RX500 S7



General installation instructions are supplied by E-Mail.



Further memory options for Fujitsu Primergy RX500 S7

Size	SKU	Technology	Туре	Number of pins	Brand	Reference no.
4GB	SP156111	DDR3	UDIMM ECC (ECC unbuffered)	240 Pin DIMM	PHS-memory®	
8GB	SP156117	DDR3	RDIMM (ECC Registered)	240 Pin DIMM	PHS-memory®	
8GB	SP156112	DDR3	UDIMM ECC (ECC unbuffered)	240 Pin DIMM	PHS-memory®	
16GB	SP156115	DDR3	RDIMM (ECC Registered)	240 Pin DIMM	PHS-memory®	
32GB	SP463993	DDR3	RDIMM (ECC Registered)	240 Pin DIMM	PHS-memory®	
32GB	SP156114	DDR3	LRDIMM (ECC LR DIMM)	240 Pin DIMM	PHS-memory®	

PHS-memory® warranty

Every PHS-memory® is equipped with a 5-years-warranty of perfect operation. If the RAM module is defective or fails within 5 years of purchase when used properly, you will receive an appropriate RAM module free of charge. If a suitable memory module is no longer available, we will refund the purchase price.

For more information on warranty and service please visit https://www.phs-memory.fr/-W5Y



Contact Information

PHS-electronic gmbh - www.phs-memory.fr -Karl-Götz-Str. 5 97424 Schweinfurt Allemagne

Phone: +49 9721 784678 E-Mail: info@phs-memory.fr Web: www.phs-memory.fr

All information without guarantee. Technical changes and errors excepted. You can find current price information in our online shop at https://www.phs-memory.fr